



## Main Features:

- ✓ Supply Voltage 230V AC (24V DC Optional)
- ✓ On & Off Time Adjustable by Single Turn Potentiometer
- ✓ Relay Output of 230V AC Or 24V DC
- ✓ Standard No. Of Channel 10 Nos. (others optional)
- ✓ Channel Termination Using Dip Switch
- ✓ Channel Status Indicated By Red LED as well as 7 Segment Display
- ✓ Clock Signal Indicated By Green LED
- ✓ Each Channel Output Is Protected By Glass Fuse
- ✓ On Board Auto / Manual Selection Option
- ✓ "Pulse" Button Individual Channel Checking
- ✓ For Handshaking With PLC, 1 No. NO Contact Present Here

## Function

For controlling the cleaning cycle of pulse jet bag filter we introduce these bag filter controller/ sequential timer card. For better performance & longevity out put of the card is relay.

## Specification

Control Supply	: 230V AC / 110V AC / 24V DC
No. Of Channels	: 10 Nos.
Channel ON Indication	: 7Segment RED FND, IN14.3mm Height.
On Time	: 01 to 200m Sec. (Adjustable)
Off Time	: 01 to 60 Sec. (Adjustable)

## Terminal Connection Diagram

