

Blue Digital Duplicator

Multi functional, more flexible.

Blue, OA Leader Blue Digital Duplicator

	ı ı
Specifica	tions
Operation mode	Scanner mobile scanning, thermal master making, memory print, A3 scan, A3 print
Scan mode	Book scan
Original type	Sheet, Book (< 10kg), Two in one
Image processing mode	Text/Text&Picture/Picture&Text/Picture/Screen/Newspaper/Pencil
Original size(min/max)	Max: 310*432mm
Printing area(max)	291*414mm
Paper size(min/max)	Min: 90*140mm Max: 310*432mm
Master making speed	19s (A4 vertical)
Resolution	300*600dpi
Print reproduction Ratio	Reductions:71%,81%,87%,94%; Enlargements;100%,115%,122%,141%, Free zoom:50~200%(1% increment)
Paper weight(min/max)	40~200g/m²
Paper feeding capacity	1000 sheets(70g/m²)
Paper receiving capacity	1500 sheets(70g/m²)
Print speed	Five Steps Variable (55/70/85/105/130 ppm)
Image positioning	Horizontal: ± 10mm, Vertical ± 10mm
Scan density	5 variable ( lighter, light, middle, dark, darker)
Master making density	5 variable ( lighter, light, middle, dark, darker)
Master eject capacity	50 sheets
	Automatically , 600ml/bottle
Stencil supply	Automatically , 90m/roll
Power source	220V, 50/60Hz
Rated input power	120W
Paper feeding system	Double roller feeder
Features	PC-connected printing, ink-saving mode, Pencil mode, Newspaper mode, Screen mode, Book Shadow erasure Programmed Printing Confidentiality mode, Code mode, Consumable used-out reminder, Auto checking the original Energy-saving function, Print contrast adjustment, The original scanning adjustment, Stencil length adjustment.
Optional function	Auto shut off, Network printing function, Auto-print pressure adjustment, U-disk master making
Optional parts	Sorter, Color drum, Bottom stand
Notice	

We keeps continuous improvement on product performance and reserves the right to amend the specification and appearance without prior notice.

Tips:- It may break down the machine if using the fake or low-quality consumable manufacturer is not responsible to supply aftersaleservice.

Please use factory's original supplies.

Please operating under the guidance of user manual.















